

## Power supply | CHROME II

DIN-mounted power supplies with double insulation Class 2 | Output current 0.63A to 7.1A | Efficiency up to 92% | AC input voltage | Screw terminal

Article:	CHROME
Brand:	Delta Electronics
Input voltage AC:	85-264V
Output voltage DC:	5V   12V   24V   48V
Output current	0.63A   1.25A   1.5A   1.92A   2A   2.4A   2.5A   3.83A   4.5A   7.1A
Effect:	12W   15W   24W   36W   54W   60W   85.2W   92.16W   91.92W
Connection:	Screw connection
Other:	Double insulated NEC Class 2



### Description

Power supply / CHROME II, mounted on DIN rail. With Class II double insulation, no earth connection is required. Its universal AC input voltage range and full power up to 55°C means that the power does not derate over the entire input voltage range. With an efficiency of up to 92%, it can be installed in compact cabinets. Its low earth fault current of less than 0.25 mA @ 264 Vac and compliance with harmonic current IEC/EN 61000-3-2, class A, guarantees safety and reliability. It is also safety approved according to IEC/EN/UL 60950-1, IEC/EN/UL 62368-1 and UL 508.

- Efficiency up to 92%
- Class II, Double Isolation (No Earth connection is required)
- Universal AC input voltage range and full power up to 55°C
- Power will not de-rate for the entire input voltage range
- Efficiency > 86.0% @ 115 Vac & 230 Vac
- Can be installed in compact cabinets
- Low earth leakage current < 0.25 mA @ 264 Vac
- Conforms to harmonic current IEC/EN 61000-3-2, Class A
- Safety approval according to IEC/EN/UL 60950-1, IEC/EN/UL 62368-1 and UL 508



## Article number

Art.No	Description	Input Voltage Range	Output voltage	Output Current	Capacity	Width mm	Height mm	Depth mm	Unit	Pc
DRC-05V015W1RZ	Power supply   CHROME II	85-264V AC	5V DC	2.4A	12W	18	87.5	55	st	1
DRC-05V030W1RZ	Power supply   CHROME II	85-264V AC	5V DC	3A	15W	35	87.5	55	st	1
DRC-12V015W1RZ	Power supply   CHROME II	85-264V AC	12V DC	1.25A	15W	18	87.5	55	st	1
DRC-12V030W1RZ	Power supply   CHROME II	85-264V AC	12V DC	2A	24W	35	87.5	55	st	1
DRC-12V060W1RZ	Power supply   CHROME II	85-264V AC	12V DC	4.5A	54W	52.5	87.5	55	st	1
DRC-12V100W1RZ	Power supply   CHROME II	85-264V AC	12V DC	7.1A	85.2W	70	87.5	55	st	1
DRC-24V015W1RZ	Power supply   CHROME II	85-264V AC	24V DC	0.63A	15W	18	87.5	55	st	1
DRC-24V030W1RZ	Power supply   CHROME II	85-264V AC	24V DC	1.5A	36W	35	87.5	55	st	1
DRC-24V060W1RZ	Power supply   CHROME II	85-264V AC	24V DC	2.5A	60W	52.5	87.5	55	st	1
DRC-24V100W1RZ	Power supply   CHROME II	85-264V AC	24V DC	3.83A	91.92W	70	87.5	55	st	1
DRC-48V060W1RZ	Power supply   CHROME II	85-264V AC	48V DC	1.25A	60W	52.5	87.5	55	st	1
DRC-48V100W1RZ	Power supply   CHROME II	85-264V AC	48V DC	1.92A	92.16W	70	87.5	55	st	1